

SWITCH ON TO SAFETY

FOR WHEN IT REALLY COUNTS

With RAFI, you will find the right emergency stop pushbutton for your application. Be it small or big, round or square, reset by pulling or rotation, rugged or design-oriented – we've got what you need. Always with our customary reliability and quality.



TECHNICAL DATA

→	Product	Highlights	Panel cut-out	Depth behind panel with contact block	Reset by	Contacts	Rated voltage/ Rated current	Terminals	Degree of protection DIN EN 529	Illumination
NEW	LUMOTAST 16	Extremely compact, always secure. Optional illuminable for night design	Ø 16.2 mm	16 mm	rotation	1 NC, 2 NC 2 NC + 1 NO	35 V / 100 mA	quick connector 2.8 x 0.8 mm, solderable	IP 67	optional
	LUMOTAST 25	Elegant and compact. Square collar, reverse polarity protected flat ribbon cable connection	Ø 16.2 mm	30.7 mm	pulling	2 NC	25 V / 100 mA	quick connector / flat-ribbon cable or PCB plug-in socket	IP 65	no
NEW	LUMOTAST 22	Compact design. Night design with illuminated arrows, optional: signal contact at 2 NC + 1 NO	Ø 22.3 mm	17.6 mm	rotation	2 NC 2 NC + 1 NO	250 V / 2.5 A	quick connector 2.8 x 0.8 mm solderable	IP 65	optional illumination of arrows
	RAFIX 16 standard	Standard for 16.2 mm panel cut-out. Optional: contact block with coupling monitoring for additional security	Ø 16.2 mm	44.7 mm (quick connect) 51.3 mm (screw terminals) 47 mm (PCB)	rotation	1 NO, 1 NC, 2 NO, 2 NC, 1 NC + 1 NO 2 NC + 1 NO	35 V / 250 mA (Au) 250 V / 6 A (Ag)	quick connector 2.8 x 0.8 mm solderable, screw terminals, PCB-plug-in socket	IP 65	no
	RAFIX 16 large	Extremely large actuation surface for reliable switching. Optional: contact block with coupling monitoring for additional security	Ø 16.2 mm	44.7 mm (quick connect) 51.3 mm (screw terminals) 47 mm (PCB)	rotation	1 NO, 1 NC, 2 NO, 2 NC, 1 NC + 1 NO 2 NC + 1 NO	35 V / 250 mA (Au) 250 V / 6 A (Ag)	quick connector 2.8 x 0.8 mm solderable, screw terminals, PCB-plug-in socket	IP 65	no
	RAFIX 16 F	Round and square design. Optional: contact block with coupling monitoring for additional security	Ø 22.3 mm □ 23.1 mm	51.7 mm (quick connect) 58.3 mm (screw terminals) 54 mm (PCB)	rotation	1 NO, 1 NC, 2 NO, 2 NC, 1 NC + 1 NO 2 NC + 1 NO	35 V / 250 mA (Au) 250 V / 6 A (Ag)	quick connector 2.8 x 0.8 mm solderable, screw terminals, PCB-plug-in socket	IP 65	no
	RAFIX 22 QR illuminable	The standard in the control cabinet. Suitable for heavy currents, numerous approvals, optional: illuminated window for night design or mechanical switching position indication	Ø 22.3 mm	39.5 mm	rotation, pulling	1 NO, 1 NC, 2 NO, 2 NC, 1 NC + 1 NO 2 NC + 2 NO 2 NC + 1 NO 2 NO + 1 NC	35 V / 100 mA (Au) 250 V / 10 A (Ag)	quick connector 6.8 x 0.8 mm solderable, screw terminals, spring type terminals	IP 65	alternatively to switching position indicator
	RAFIX 22 QR with lock	The standard in the control cabinet. With 'master key' for resetting of activated push-button, suitable for heavy currents, numerous approvals	Ø 22.3 mm	39.5 mm	rotation, pulling	1 NO, 1 NC, 2 NO, 2 NC, 1 NC + 1 NO 2 NC + 2 NO 2 NC + 1 NO 2 NO + 1 NC	35 V / 100 mA (Au) 250 V / 10 A (Ag)	quick connector 6.8 x 0.8 mm solderable, screw terminals, spring type terminals	IP 65	no
	RAFIX 22 FS+ standard	The standard with opaque mushroom head. Also available with increased protection class IP 69K or with 2 NC + 1 NO contact, combinable with all RAFIX FS emergency stop contact blocks	Ø 22.3 mm	27 mm (quick connect) 9.2 mm (PCB)	rotation, pulling	1 NO, 1 NC, 2 NO, 2 NC, 1 NC + 1 NO 2 NC + 1 NO	35 V / 100 mA (Au) 250 V / 4 A (Ag)	quick connector 2.8 x 0.8 mm solderable, PCB	IP 65 (rotation) IP 69K (pulling)	optional by center window
	RAFIX 22 FS+ compact	Elegant and compact. Night design with illuminated arrows, LUMOTAST 22 design style with modular construction, combinable with all the RAFIX 22 FS emergency stop contact blocks	Ø 22.3 mm	27 mm (quick connect) 9.2 mm (PCB)	rotation	1 NO, 1 NC, 2 NO, 2 NC, 1 NC + 1 NO	35 V / 100 mA (Au) 250 V / 4 A (Ag)	quick connector 2.8 x 0.8 mm solderable, PCB	IP 65	arrows
NEW	RAFIX 22 FS+ design	Design version with star design and optional mechanical switching position indication. Combinable with all RAFIX FS emergency stop contact blocks	Ø 22.3 mm	27 mm (quick connect) 9.2 mm (PCB)	rotation	1 NO, 1 NC, 2 NO, 2 NC, 1 NC + 1 NO	35 V / 100 mA (Au) 250 V / 4 A (Ag)	quick connector 2.8 x 0.8 mm solderable, PCB	IP 65	alternatively to switching position indicator
	RAFIX 22 FSR plastic mushroom head	Rugged model with metal body and plastic mushroom head. Optional: illuminable windows, combinable with all RAFIX FS emergency stop contact blocks	Ø 22.3 mm	27 mm (quick connect) 9.2 mm (PCB)	pulling	1 NO, 1 NC, 2 NO, 2 NC, 1 NC + 1 NO	35 V / 100 mA (Au) 250 V / 4 A (Ag)	quick connector 2.8 x 0.8 mm solderable, PCB	IP 65 IP 69K	optional by center windows
	RAFIX 22 FSR metal mushroom head	Rugged model with top design and metal mushroom head. Combinable with all RAFIX FS emergency stop contact blocks	Ø 22.3 mm	27 mm (quick connect) 9.2 mm (PCB)	pulling	1 NO, 1 NC, 2 NO, 2 NC, 1 NC + 1 NO	35 V / 100 mA (Au) 250 V / 4 A (Ag)	quick connector 2.8 x 0.8 mm solderable, PCB	IP 65 IP 69K	optional by center windows
NEW	RAFIX 22 FSR gaiter	Rugged model with dirt deflector for extremely dirty environments. Washable with high pressure, combinable with all RAFIX FS emergency stop contact blocks	Ø 22.3 mm	27 mm (quick connect) 9.2 mm (PCB)	pulling	1 NO, 1 NC, 2 NO, 2 NC, 1 NC + 1 NO	35 V / 100 mA (Au) 250 V / 4 A (Ag)	quick connector 2.8 x 0.8 mm solderable, PCB	IP 65 IP 69K	optional by center windows